

GALCON BLUETOOTH 9001BT BATTERY OPERATED TAP TIMER

Galcon's Bluetooth 9001BT is a user - friendly, single station tap timer. The 9001BT is made for use to irrigate home gardens, drip and sprinkler systems, flower pots roof gardens and flowerbeds.

FEATURES

- 9001BT - 20mm / 25mm Tap Timer with Bluetooth programming
- Use free app to program and manually operate the valve
- Program the controller with or without your smartphone
- Operated with 1 x 9v alkaline battery (not included)
- Run times from 1 minute - 12 hours
- Four start times per day
- 7 day programming or 1 - 30 day interval
- Manual activation at controller
- Rain off suspension option
- Rain sensor override ready
- Low battery indicator
- Compatible with IOS7 and Android 4.3

TECHNICAL SPECIFICATION

- Power 1 x 9v alkaline battery (not included)
- Maximum flow 20 Lpm
- Minimum flow 1 Lpm
- Maximum working pressure 1000kPa
- Minimum working pressure 100 kPa
- Rain sensor shutdown

PAIR THE CONTROLLER WITH THE GALCONBT APP

- Download and install the GalconBT app from Google Play or the App Store
- Insert one 9V alkaline battery to the controller battery compartment
- Enable Bluetooth on your device (make sure its visible or discoverable)
- Launch the GalconBT App
- Enter your unique 4 digit code displayed on the 9001BT screen



9001BT



This product is used on cold water irrigation systems only and installed outdoors

MODELS	CODE
20mm / 25mm Tap timer with Bluetooth programming	9001BT
9 volt alkaline battery	9V-ALK-B
Rain sensor connects to 9001BT series for rain shut down	RX-1

